



Quick Guide: Simon XT Touch Screen



For a detailed review of the entire system, please view the [Simon XT Touch Screen system manual](#).

Arm and Disarm

Arm:

- To arm in **AWAY** mode when you are leaving the premises, select the [ARM] button from the home screen, then select the [Arm All] button.
- To arm in **STAY** mode when you are not leaving the premises, select the [ARM] button from the home screen, then select the [Arm Doors + Windows Only] button.

Disarm:

- To **disarm**, select the [DISARM] button from the home screen, then enter your [security code].

Bypassing Protected Areas

Bypassing a zone allows you to arm your system with certain protected areas intentionally unarmed or to access a protected area when the system is armed.

- To **bypass** a zone, select the [OPTIONS] button from the home screen.
- Select [Direct Bypass] and enter your [master security code].
- For each sensor you wish to bypass, select the [BYPASSED] button.

- To **unbypass** a zone, select the [DISARM] button from the home screen, then enter your [security code].

Change Time and Date

To access date and time settings, press the [STATUS & SETTINGS] button from the home screen.

- Select the [Date/Time] button and enter the [master security code].
- To set the **time**, enter the time in the hour/minute format, then press [SAVE].
- Toggle between [a.m.] and [p.m.], then press [SAVE].

- To set the **date**, enter the date in the month/date/year format, then press [SAVE].
- Select the [CLOSE] button to exit through the menus back to the home screen.

Chimes and Beeps

Your system communicates events using chimes and beeps whenever a protected door or window is opened.

- To **silence or enable chimes**, select the [STATUS & SETTINGS] button from the home screen.
- Scroll down until you reach the [Chime] button.
- Touching the button toggles between Chime On and Chime Off.
- Select the [CLOSE] button to exit through the menus back to the home screen.

Reset

It is recommended that you clear the system status after an alarm event.

- To clear and reset the system status, select the [STATUS & SETTINGS] button on the home screen.
- Select the [CLEAR] button located next to the [Panel Status] button.
- Select the [CLOSE] button to exit through the menus back to the home screen.

Security Codes

You can program up to 8 different security codes for use by other users, however only the Master user can assign user codes to users. No user, except for the Master user, can program or bypass sensors.

- To **add a user code**, select the [STATUS & SETTINGS] button from the home screen.
- Scroll until the [Programming] option is listed. Select the option by pressing the [Programming] button or pressing [Enter].
- Enter your [master security code], then press [OK].
- Select the [ACCESS CODES] button. Initially all user codes are blank.
- Use the white field next to the access code to enter a **new** access code or to **edit/delete** a current access code, then press [SAVE].
- Press [CLOSE] to close each menu until you reach the home screen.

Trouble Conditions

Trouble conditions are issues that require your attention and are indicated by six rapid beeps sounding every minute until the Trouble Condition is corrected.

- To **silence the trouble beeps**, select the [STATUS & SETTINGS] button from the home screen.
- Select the [Listen] button or arm and disarm the system. The beeping will be silenced for four hours.

For a list of possible Trouble Conditions, please see your [Simon XT Touch Screen system manual](#).

Volume

- To program the **beep volume**, select the [STATUS & SETTINGS] button on the home screen.
- A volume adjuster will be located next to the words [Beep Volume].
- Press the left arrow to lower the beep volume and the right arrow to raise the beep volume.

- To program the **piezo beeps**, select the [STATUS & SETTINGS] button on the home screen.
- Select the [SIREN OPTIONS] and toggle between the On and Off settings. A check mark indicates the selected option.
- Select the [CLOSE] button to exit.

- To program the **piezo alarms**, select the [STATUS & SETTINGS] button on the home screen.
- Select the [SIREN OPTIONS] and toggle between the On and Off settings. A check mark indicates the selected option.
- Select the [CLOSE] button to exit.

- To program the **panel voice** select the [STATUS & SETTINGS] button on the home screen.

- Select the [SIREN OPTIONS] and toggle between the On and Off settings. A check mark indicates the selected option.
- Select the [CLOSE] button to exit.



